

SUPREMA[®]Touch

Modular Fire & Gas Detection System



Fire & Gas Detection Solutions

The modular design of the SUPREMATouch Fire and Gas Detection System meets the requirements of a diverse range of industries and applications, while complying with all relevant global safety standards. The system builds on the success of the original innovative SUPREMA Control System design and features a large color touchscreen display, enhanced processing capabilities, and optional integration of addressable fire and smoke detectors. It can be used with a wide range of detectors, including combustible and toxic gas, oxygen, smoke, fire and heat. Output options include relay, and analog and digital communication between racks, which allows interfacing to external systems using ModBus or Profibus.

The SUPREMATouch System's modularity enables a variety of fire and gas detection configurations that meet the requirements of virtually any application, including redundant systems with up to a Safety Integrity Level (SIL) 3 rating (IEC 61508).

Whatever the application, our strong experience in fire and gas detection enables us to provide the best combination of detectors, field devices, components and systems that will ensure reliable and secure protection of your personnel and facilities.









Modular Design for Individual Solutions

The SUPREMATouch System is compatible with all MSA fire and gas detectors and can accommodate a variety of third party devices such as 4–20 mA transmitters and heat and smoke sensors. Open-collector driver outputs (24 V, 0.3 A) provide direct control of relays or other circuit elements such as contacts, switches or solenoid valves.

With the SUPREMATouch System, digital signal transmission is possible via ModBus and Profibus. There is also an analog output option.

Designed around standard industrial 19" racks, the SUPREMATouch System provides signal processing for up to 256 inputs and 512 outputs. It also has the ability to distribute the system over up to 8 racks, using satellites to minimize installation costs. The modular design allows input and output connections to be either mounted on the backplane or DIN rail mounted. Wall-mount versions in a NEMA 4 enclosure are also available upon request.

System Flexibility

- Innovative modular assembly
- Easy checkbox selection to link measurement input with appropriate output
- Simple alarm configuration by checkbox selection including voting and grouping
- Variable and customized system layout



The user-friendly touchscreen interface makes installation, configuration, setup and operation of the SUPREMATouch System extremely simple. No programming skills are necessary. The status signals of up to 256 sensors can be linked and grouped with up to 512 outputs by selecting a checkbox with a simple touch of the display or a mouse click at a connected computer.

	-	603	SUPREMATouch
List	Bars	LEDS	•
No Tag		Value	Status
1MS01		1.3% LEL	Measure
2MS02		1.3% LEL	Measure
3MS03		1 3% LEL	Measure
4MS04		1.3% LEL	Measure
5MS05		1.5% LEL	Measure
6MS06		1 3% LEL	Measure
7MS07		1 3% LEL	Measure
8MS08		1.3% LEL	Measure
00	-		CAN A O

- Color LCD touchscreen with LED backlight
- Menu-driven graphical user interface
- Detailed diagnostics and event logging
- No programming required
- Simple parameter configuration and calibration
- Comprehensive measurement input information
- Optional user-defined sensor parameters
- Simple alarm assignment and configuration
- Digital output inhibit functions
- 3-level password security

SUPREMA Manager

MSA software is available for a USB-connected computer. This is especially useful during setup and regular sensor calibration of larger systems. The software enables all the functions available at the SUPREMATouch System display, such as configuration and calibration, offline use, and the storing and printing of reports as PDF documents. This provides a user-friendly environment for configuration (*see screen view image*), parameter setting, and sensor calibration of large systems to minimize the cost of maintaining the SUPREMATouch System.

Settings Extra Info					3) s	UPREMA	Manag	er Z	0)								The Sa	fety Comp
EMA Data Selection		Con	figura	tion >	Syster	m > ⊦	lardwar	re													
New Location	Opera	tion Mod	se: Stan	dard	Y																
EMA Connection		Ŧ	Add re	ck [-		Gateway (Gateway (CAN A) CAN A)		ID: 124			Active Active	Ga	ateway (C	CAN B) CAN B)		ID: 125 ID: 127	~		ctive
Access X 1 2 3 4	Rack	MCP 1	MCP 2	MCP 3	MDA 1	MDA	2 MAI MGO MAO MBC	MAI MGO MAO MBC	MAI MGO MAO MEC	MAI MGO MAO MBC	MAI MGO MAO MBC	MAI MGO MAO MBC	MAI MGO MAO MBC	MAI MGO MAO MBC	MGO MAO MBC	MGO MAO MBC	MDO	Power Supply	Power Supply	Power Supply	Delete
Computation		Slot 1	Slot 2	Slot 3	Slot 4	Slot 5	5 Slot 6	Slot 7	Slot 8	Slot 9	Slot 10	Slot 11	Slot 12	Slot 13	Slot 14	Slot 15		Internal	External	Battery	
figuration System	1	MCP A1	MCP 8.2		MDA A4	MDA 85	MAI	MAI	MAR	MAI MAR	MAJ	MAI MAR	MAI MAR	MAI	MGO A 14	MGO B 15					
Sensor Heads					MDA	MDA	MAI	MAT	MAL	MAI	MAI	MAI	MAI	MAL	MGO	MGO		-	-	-	-
Books	2				A 20	8 21	MAR	MAR	MAR	MAR	MLAR	MAR	MAR	MAR	A 30	8.31					
Pre-Adjustments	3				MDA	MDA	MAI	MAI MAR	MAI MAR	MAJ MAR	MAI MAR	MAI MAR	MAI MAR	MAI MAR	MGO	MGO					8
System Events	-				MIT			MAX							MCO	MCO					
Alarm Events	4				A 52	8 53	MAR	MAR	MAR	MAR	MAR	MAR		MAR	A 82	0.63			V		8
Parameter Changes	5						MGO	MGO	MGO	MGO	MGO	MGO	MGO	MGO	MGO						
Brocesseor Temperatures							A 70	A71	A 12	A 73	A 74	A 75	A 70	K II	A 78						
ntenance	6						MGO 8 88	MGO 8 87	B BS	B 89	MGO B EO	MGO 8 91	MGO B 92	MGO 8 93	BIH						
Interface Tests	7						MAO A 102	MAO A 103	MAO A 104	MAO A 105	MAO A 105	MAO A 107	MAO A 100								
Alarm Suppressions Change Passwords Synchronize System Time	8				MDA A 115	MDA 8 117								MAJ MAR					V		8
Printer Settings																					,

Made-to-Measure Safety

The SUPREMATouch System provides control capability to meet the user's safety requirements. The modular system allows I/O (Input/Output) connections to be either rail- or back-plane-mounted, to be configured as desired and to be adapted to meet each specific monitoring task.

All system functions can be controlled by the SUPREMATouch System, including I/O inhibition, alarm activation, analog output signals, I/O fault handling, voting allocation management of status signals and switched outputs, control of annunciation panels and devices such as fans and dampers. The unit can also interface with other systems (HVAC, ESD, etc.) through digital bus communications.

The digital bus technology of the SUPREMATouch System ensures reliable communication between racks and provides the flexibility of being able to have up to 8 satellite racks per system located at distances up to 1.2 km apart. This ensures that system wiring is minimized, and that overall system costs are as low as possible.

Features	Benefits
Compact modular design requires fewer cabinets	Saves space
Decentralized configuration	Use of satellites minimizes wiring
Plug-in ribbon cables	Easy installation and system extension
Future-oriented technology	Reduces upgrade costs
Digital bus technology	Reliable communication to external bus systems
 System configuration by checkbox selection 	No programming skills required
Connections for 3 system power supplies	 Automatic switchover to backup supply

The SUPREMATouch System also interfaces to external bus systems such as ModBus and Profibus.





The SUPREMATouch System is certified to all relevant fire and gas detection standards.













Technical Specifications

Enclosure	Standard 19" rack (up to 8 racks per system) Optional NEMA 4 wall-mount cabinet
System	Satellites for decentralized input and outputs up to a distance of 1.2 km Optional redundant configuration Event and fault diagnosis logging
Inputs	Up to 256 per system Up to 64 per rack
Outputs	Up to 512 per system Up to 80 per rack Switched open-collector driver (24 V, 300 mA) Relays – SPCO or SPST redundant (230 V, 3 A) Optional solid state relays for low-current applications Software control of switched outputs/relays: group creation n out of m alarms alarm multiplication
Power supply	Operating voltage: 18 to 32 VDC Optional rack power supply – 85 to 265 VAC, 150 W, 50/60 Hz Power supply connections for internal, external, and battery backup (24 VDC) with automatic switch-over
Display	Color LCD touchscreen with backlight 5.7" TFT with 320 x 240 resolution
Controls and indicators	Alarm reset and acknowledge keys Front panel LEDs for alarms 1, 2, 3 and 4, signal fail, inhibit, power and system fail 3-level password or keyswitch for secure access control
Sensors	Catalytic or IR for combustible 4–20 mA transmitters Electrochemical for toxic and oxygen Conventional smoke, heat and fire detectors Addressable smoke, heat and fire detectors via external fire panel
Approvals	ATEX (EN 50104, EN 50271, EN 61779-1, EN 61779-4, EN 61779-5) CSA / CSA us SIL 3 (EN 50402, EN 61508) GB16808-2008 Combustible Gas Alarm Control Units (China)
Interfaces	Optional interfaces to external bus systems (ModBus RTU and TCP, Profibus) 2 x RS-232 and 1 x USB electrically isolated interfaces for data transfer Printer report of system events (standard ASCII, 80 CHR)

Detailed ordering information available upon request.



Ordering Information

Inputs

of Analog # of Discrete

of Relay Outputs

(First 8 relays common; 80 maximum - rail mount)

Mounting Style

A = 4-20 mA Rail Mount B = 4-20 mA Back Mount

Power Supply

0 = None 1 = 150 W, 85–265 VAC (Internal)

Safety Integrity

S = SimplexD = Duplex

Bus Interface

0 = None M = ModBus RTU P = Profibus DP T = ModBus TCP

Custom Features

0 = None C = Custom ST = Satellite S3 = TUV SIL 3 Certification

Rail Mount or Back Mount

Number of Sensors* Number of Relays* *Must be ordered in multiples of 8.

Accessories

NEMA 4 Wall-mount Cabinet 8 Analog Outputs Satellite (duplex) External Power Supply DIN Rail 240 W 480 W

Call MSA for detailed pricing information based on your application.



MSA, the Global Leader in Safety



MSA's passion for safety comes from almost a full century of manufacturing the highest quality gas monitoring instruments. MSA designs and manufactures a complete line of flame and gas detection products for oil, gas, and petrochemical applications. Our passion shows through in our all-stainless-steel, globally-approved flame and gas detection fixed-gas instruments, and our reliable and durable single-gas and multigas portable instruments.

MSA is dedicated to designing and manufacturing superior flame and gas monitoring instruments to help ensure that men and women may work in safety, and that they, their families, and their communities may live in health throughout the world. Providing the best products, service, and support in the industry: that's MSA's passion.





Global Reach

MSA is the largest company in the world dedicated solely to producing a complete range of equipment and systems for worker and plant protection. With headquarters located in Cranberry Township, Pennsylvania, our operations extend around the world. Our vast resources ensure that an MSA affiliate is never far away and help to maintain our commitment to protecting lives in more than 120 countries, on all continents around the globe.

Local Presence

MSA-authorized representatives comprise one of the largest distribution networks, providing comprehensive sales, service, and support. MSA field sales representatives and service technicians are thoroughly trained in the use, application, and servicing of our products. With MSA, you have access to dedicated and highly-trained field staff as well as support within our Customer Service Center. Engineers, architects, and operators find flame and gas detection products to suit their every need, with the superior reliability, durability, and design excellence expected from MSA.

Got to www.MSAsafety.com/SUPREMAtouch or call Customer Service 1.800.MSA.INST for more information on the SUPREMATouch System.

Note: This bulletin contains only a general description of the products shown. While uses and performance capabilities are described, under no circumstances shall the products be used by untrained or unqualified individuals and not until the product instructions including any warnings or cautions provided have been thoroughly read and understood. Only they contain the complete and detailed information concerning proper



MSA Corporate Center 1000 Cranberry Woods Drive Cranberry Township, PA 16066 USA 724-776-8600 Phone www.MSAsafety.com

U.S. Customer Service Center Phone 1-800-MSA-INST Fax 1-800-967-0398

MSA Canada Phone 1-800-MSA-INST Fax 1-800-967-0398 MSA Mexico

01 800 672 7222 Phone 52-44 2227 3943 Fax MSA International Phone 724-776-8626

Toll Free 1-800-672-7777 FAX 724-741-1559





ID 07-20135-MC / June 2012 © MSA 2012 Printed in U.S.A.

use and care of these products.